

Amendments to the Claims:

This listing of claims will replace all prior versions, and listings, of claims in the application:

Listing of Claims:

1. (currently amended): A logic circuit for use in a multiplexer to shift data, comprising:

a plurality of dual rail Domino logic gates, each logic gate receiving data inputs and control signals, wherein each data input line is connected only to ~~has a one-to-one correlation to~~ a single data transistor, and wherein the control signals include a plurality of control lines to provide for multiple shifting operations; and

a plurality of shared data lines connecting the logic gates, the shared data lines providing a portion of the data inputs for each of the logic gates by connecting data inputs among the plurality of logic gates,

wherein the logic gates shift data received at the data inputs based upon the control signals and the connections of the shared data lines to produce a shifted data output, and wherein all of the plurality of logic gates share a single data transistor for each data input, and wherein each of the logic gates receives one data input using the single data transistor and receives other data inputs from adjacent logic gates using the plurality of shared data lines to reduce the number of data transistors required.
2. (original): The logic circuit of claim 1 wherein each of the logic gates includes first and second stages of shifting performing first and second shift operations.
3. (original): The logic circuit of claim 2 wherein each of the logic gates includes control inputs for receiving two sets of shift control signals for the first and second stages of shifting.
4. (original): The logic circuit of claim 3, further including another plurality of shared data lines for providing data inputs to the second stage of shifting for the second shift operation.
5. (cancelled).
6. (original): The logic circuit of claim 1 wherein each of the logic gates receives as one of the data inputs a primary data line.
7. (original): The logic circuit of claim 1 wherein each of the logic gates receives a clocking signal for enabling the logic gates to feed data.

8. (original): The logic circuit of claim 1 wherein each of the logic gates includes a plurality of transistors, controlled by the control signals, for feeding data from the shared data lines into the logic gate.

9. (original): The logic circuit of claim 1 wherein each of the logic gates provides complementary outputs as the shifted data output.

10. (original): The logic circuit of claim 1 wherein each of the shared data lines connects one of the logic gates with a plurality of the logic gates.

11. (currently amended): A method of using a multiplexer to shift data, comprising:

providing a plurality of dual rail Domino logic gates each receiving data inputs and control signals, wherein each data input line is connected only to ~~has a one-to-one correlation to~~ a single data transistor, and wherein the control signals include a plurality of control lines to provide for multiple shifting operations;

connecting the logic gates using a plurality of shared data lines, wherein the plurality of shared data lines providing a portion of the data inputs for each of the logic gates by connecting data inputs among the plurality of logic gates; and

shifting data received at the data inputs by one or more data bits based upon the control signals and the connections of the shared data lines to produce a shifted data output, wherein all of the plurality of logic gates share a single data transistor for each data input, and wherein each of the logic gates receives one data input using the single data transistor and receives other data inputs from adjacent logic gates using the plurality of shared data lines to reduce the number of data transistors required.

12. (original): The method of claim 11 wherein the shifting step includes shifting the data through first and second stages of shifting performing first and second shift operations.

13. (original): The method of claim 12 wherein the providing step includes receiving two sets of shift control signals for the first and second stages of shifting.

14. (original): The method of claim 13, further including connecting the logic gates using another plurality of shared data lines for providing data inputs to the second stage of shifting for the second shift operation.

15. (cancelled).

16. (original): The method of claim 11 wherein the providing step includes receiving as one of the data inputs a primary data line.

17. (original): The method of claim 11 wherein the providing step includes receiving a clocking signal for enabling the logic gates to feed data.

18. (original): The method of claim 11 wherein the shifting step includes feeding data from the shared data lines into the logic gates using transistors controlled by the control signals.
19. (original): The method of claim 11 wherein the shifting step includes providing complementary outputs as the shifted data output.
20. (original): The method of claim 11 wherein the connecting step includes connecting one of the logic gates with a plurality of the logic gates.